Prime2RP

Reduced Power Infrared Gas Sensor

Reduced-power infrared Carbon dioxide measurement — 15 mA average typical operating current, with 0.4–2.0 V linear voltage output.



0–5 % vol
Normal measuring range

15 mA
Average typical operating current

3.0–5.0 V
45 mW typical power at 3.0 V supply

01 Key Features

- **Operates independent of supply polarity** — simple, polarity-independent integration
- 0.4–2.0 V linear voltage output plus UART serial communications
- **Sensing ranges** — 0–5000 ppm CO_2 up to 0–10 % volume CO_2
- **Flexible electronic configuration access** — wide operating temperature range
- **Microprocessor-generated linear voltage output** — independent of supply polarity
- **Operating voltage range 3.0 V – 5.0 V** — 15 mA average typical operating current
- **All metal construction with isolated housing** — small internal volume
- **Fast response** — immunity from 'poisoning'

02 At a Glance

ITEM	SPECIFICATION
Target gas	Carbon dioxide
Measuring ranges	0–5000 ppm CO_2 up to 0–10 % volume CO_2
Minimum resolution	At zero < 0.5% of range. At range<2% of range
Output formats	linear voltage, serial communications
Supply voltage	3.0 V – 5.0 V (15 mA average typical)
Response time (T90)	< 30 s
Operating temperature	–30 °C to +50 °C
Weight	18.0 g
Approvals / IP	Not Ex approved; house in a suitable Ex enclosure in hazardous areas
Patent	GB2449433

Operation & CO_2 response

03 Description and Operation

The Prime2RP sensor uses the non-dispersive infrared method to detect the presence of carbon dioxide. The sensor contains an infrared radiation source, a dual element custom infrared detector, a unique optical waveguide into which gas diffuses and internal microprocessor-based electronics to provide a voltage output which is independent of the power supply polarity.


The sensor provides a linear voltage output, typically 0.4 V – 2.0 V over range with respect to the negative supply pin. In addition, the output can be read and the internal configuration can be accessed by a serial communication link. The communication link contacts are pads in the 3-pin version Prime2RP. The linear voltage output is referenced to the negative supply pin and is independent of supply polarity.

The internal electronics perform all the functions of driving the optical parts of the sensor, extracting the detector signals, converting the signals to a concentration, applying temperature compensation and scaling the output. The Prime2RP is not currently Ex approved so should be housed in a suitable Ex enclosure when used in hazardous areas.

Technical support on implementation and application notes are available from Clairair Limited.

04 Pin Allocation (5-pin version)

All dimensions in millimetres (±0.1 mm unless noted). Rx and Tx are pads in the 3-pin format. The sensor body is an all-metal construction with an isolated housing and a small internal volume. Mechanical outline drawings, 3-pin and 5-pin footprint details, and recommended PCB socket information are available from Clairair on request.



05 Carbon Dioxide Response Characteristics

Unless otherwise specified, the Prime2 is calibrated during manufacture to provide an output signal linearised over the specified carbon dioxide range.

CALIBRATION OPTIONS

0–5000 ppm Small range	**0–5** % vol CO_2 Standard sensing range	**0–10** % vol CO_2 Extended range available	**CO_2** Dedicated detection

Dedicated to carbon dioxide detection. For hydrocarbon or methane applications, use PrimePell or PrimePellRP. Typical response characteristics are available from Clairair on request.

Performance & diagnostics


06 Performance and Diagnostics

6.1 Temperature Compensation

The Prime2RP is temperature compensated for both zero and span at the calibration gas concentration level.

6.2 Sensor Warm-up

When power is first applied or when a reset has occurred or during automatic recovery from a fault condition the Prime2RP outputs −1.56 % of scale (0.375 V in voltage mode) for 5 seconds then outputs 0 % of scale for a warm-up period (default is 15 seconds). After this time the output follows the extracted gas value.



6.3 Fault Indication

The sensor continuously monitors several internal parameters to ensure that the internal hardware and software are operating correctly. If a fault condition is detected, the output is set to 0 V. Some faults are recoverable (for example a brown-out in the incoming supply voltage) and the sensor continuously checks for possible recovery. If a fault can be recovered from, the output follows the sensor warm-up sequence before following the extracted gas value.

6.4 Reliability — Failure Modes Effects and Diagnostic Analysis (FMEDA)

An FMEDA on the Prime2RP produced the following summary results.

ITEM	VALUE	ITEM	VALUE
Conditions	Ground fixed, JAN to MILHDBK217F	λSD	921 FIT
Subsystem type	B (complex, using microcontrollers or programmable logic)	λSU	3 FIT
Hardware fault tolerance	0	λDD	859 FIT
Mode	High demand (continuous use of operation)	λDU	96 FIT
Probability of dangerous failure per hour	9.5×10^{-7}	SFF	94.9 %

07 Output Formats

The Prime2RP provides a linear voltage output independent of supply polarity.The output is not a bridge (ratiometric) output; it is a ground-referenced linear voltage generated by the internal microprocessor.

Linear voltage

0.4–2.0 V

0.4 V – 2.0 V over range with respect to the negative supply pin

Serial communications

Rx / Tx

Output can be read and the internal configuration accessed over a serial link (pads in the 3-pin version, pins in the 5-pin version)

Ratings & specification

08 Absolute Maximum Ratings

Ambient temperature range

−40 °C to +80 °C

Supply voltage (between pins 2 and 3)

5.5 V

09 Handling Precautions

Electrostatic sensitive devices

The Prime range of sensors contains electrostatic sensitive components. Anti-static handling precautions should be observed when handling these products.

Soldering and mounting

Soldering to the pins may seriously damage the sensor. Connections should be made via PCB sockets only.

- Recommended socket: Wearnes Cambion reference 450-3326-01-06-00
- 3-pin version: Rx and Tx are brought out as pads

10 Specification

Unless otherwise stated, all data was taken using: supply voltage 3.5 V; ambient temperature 20 °C to 25 °C; ambient pressure 995 hPa to 1020 hPa; gases diluted in nitrogen; gas flow rate 1 litre/min across the sensor face.

PARAMETER	VALUE
Supply voltage range	3.0 V – 5.0 V
Power consumption	45 mW typical at 3.0 V supply
Nominal ranges	0 – 5 % volume CO_2 / 0 – 5000 ppm CO_2 / 0 – 10 % volume CO_2
Default output range — voltage mode	0.4 V – 2.0 V
Warm-up time — to operation	< 60 s
Warm-up time — to specification	< 3 minutes
Response time (T90)	< 30 s to a step change in gas concentration
Minimum resolution	At zero: < 0.5 % of range / At range: < 2 % of range
Zero repeatability	± 1 % of range
Accuracy	± 3 % of range up to 50 % of range; ± 5 % of range above 50 % of range
MTBF	> 5 years
Digital interface format	8 data bits, 1 stop bit, no parity
Digital interface baud rate	38 400 (default), 19 200, 9 600
Digital interface logic levels	VINL input low: < 0.8 V / VINH input high: > 2.0 V / VOL output low: < 0.4 V / VOH output high: > 2.4 V
Weight	18.0 grams
Vibration	Complies with EN 61779-1
Relative humidity	0 – 95 % RH non-condensing
Operating temperature range	−30 °C to +50 °C
Storage temperature range	−40 °C to +80 °C
Operating pressure range	700 – 1300 hPa

In the interest of continued product improvement Clairair Ltd reserves the right to change the design features and specifications without prior notification. The data contained in this document is for guidance only. Whilst Clairair Ltd has taken care to ensure the accuracy of the information in this document it accepts no responsibility for the consequences of any use of this document or the information contained within it.

Configure your Prime2RP

11 Ordering Information

The Prime2RP is available in the configurations listed below. Please specify the required configuration when ordering.

Prime2RP / 5 / 0–5% CO_2

Range:

0-5000 ppm
0-5% vol
0-10% vol
Q =Customized

Pin number & certification:

3 =3 pins Not Ex approved
5 =5 pins Not Ex approved
3Ex =3 pins with Ex approved
5Ex =5 pins with Ex approved

All Prime Reduced Power series sensors have both serial communications and analogue voltage outputs.

Please quote the model, pin configuration, calibration gas and range, LEL basis (where applicable) and output format with your order. For custom calibrations, quantities and lead times, please contact Clairair.

12 Contact and Support

Technical support on implementation and application notes are available from Clairair Limited.

Clairair Ltd
Little Braxted Hall, Little Braxted, Witham,
Essex, CM8 3EU, U.K.

+44 (0)1376 516414
info@clairair.com

+44 (0)1376 516415
www.clairair.com

In the interest of continued product improvement Clairair Ltd reserves the right to change the design features and specifications without prior notification. The data contained in this document is for guidance only. Whilst Clairair Ltd has taken care to ensure the accuracy of the information in this document it accepts no responsibility for the consequences of any use of this document or the information contained within it.